



NOTES:

1. EVERY MODULE'S METALLIC FRAME MUST BE EARTHED BY CONNECTING THE FRAME TO THE METALLIC SUPPORTING STRUCTURE USING A 4mm² CU/PVC/PVC PE CABLE.
2. EVERY METALLIC SUPPORTING STRUCTURE MUST BE EARTHED USING A 16mm² CU/PVC/PVC PE CABLE.
3. EVERY PANELBOARD'S METALLIC ENCLOSURE AND METALLIC BACKSHEET MUST BE EARTHED USING A 4mm² CU/PVC/PVC PE CABLE.
4. ALL NEW EARTHING POINTS TO BE CONNECTED TO A NEW EARTHING SYSTEM DEDICATED FOR THE SOLAR PV SYSTEM.
5. ALL PV CABLES SIZES TO BE 10 4mm² CABLES TO BE USE SOLAR PV1-F DC CABLE (OR EQUIVALENT), 10V CERTIFIED (TDV 2 PIG 1169/08/07), CU TINNED CLASS 5 CONDUCTOR (ACC. TO IEC 60228), CROSSLINKED SPECIAL POLYOLEFIN, HALOGEN FREE, OZONE RESISTANT, WEATHER & UV-RESISTANT INSULATION & JACKET MATERIAL, 1800VDC MAXIMUM OPEN CIRCUIT VOLTAGE RATING (CONDUCTOR-CONDUCTOR, NON EARTHED SYSTEM), FLAME RETARDANT ACC. TO IEC 60332-1.
6. ALL DC POWER CABLES FROM THE BATTERY BANK TO THE INVERTER/CHARGER MUST BE 10 70 mm² UNARMORED CU/PVC/PVC, THE BATTERIES POSITIVE AND NEGATIVE BUSBARS SHALL BE WELL SEPARATED AND SECURED FOR SAFETY PURPOSES.
7. ALL AC POWER CABLES TO/FROM THE INVERTER MUST BE 4C 10mm² UNARMORED CU/PVC/PVC, 0.6/1KV AND THE CORRESPONDING PE CABLES MUST BE 1C 10mm² UNARMORED CU/PVC/PVC 0.5KV YELLOW/GREEN, ALL TO BE CONFORMING TO IEC 60502-1.
8. THE INVERTER SHALL FEED ALL LOADS EXCEPT FOR ALL SPLIT AC UNITS, WATER HEATERS, AND HEATERS. ALL NECESSARY CONTROL MEASURES SHALL BE TAKEN BY THE CONTRACTOR TO GUARANTEE THE REQUIRED LOAD SEGREGATION. THE CONTRACTOR SHALL INSTALL SEPARATE MANUAL SWITCHES ALLOWING OPERATORS TO FEED EACH OF EXCLUDED LOADS WHEN NECESSARY.
9. ALL AC POWER CABLES TO/FROM THE SOLAR DRIVE INVERTER MUST BE 2C 4mm² UNARMORED CU/PVC/PVC, 0.6/1KV AND THE CORRESPONDING PE CABLES MUST BE 1C 4mm² UNARMORED CU/PVC/PVC 0.5KV YELLOW/GREEN, ALL TO BE CONFORMING TO IEC 60502-1.
10. THE CONTRACTOR SHALL UNDERTAKE ALL REQUIRED MEASURES TO ENSURE THE PROPER INSTALLATION AND OPERATION OF THE SOLAR DRIVE INVERTER, INCLUDING BUT NOT LIMITED TO REPLACEMENT OF EXISTING WATER PUMPS WITH WATER PUMPS COMPATIBLE WITH THE SOLAR DRIVE INVERTER IF NEEDED.
11. ALL INVERTERS CABLE GLANDS OPENINGS MUST BE TIGHTLY SEALED USING THE SUPPLIED INVERTER MATERIAL TO ENSURE AN IP65 PROTECTION LEVEL.
12. A POWER METER SHALL BE INSTALLED ON THE AC OUTPUT SIDE AFTER THE MTS TO DISPLAY AT LEAST THE VOLTAGE AND CURRENT READINGS.
13. A PHASE FAILURE/COVER UNDER VOLTAGE PROTECTION RELAY WITH A NORMALLY OPEN CONTACTOR SHALL BE INSTALLED ON THE AC INPUT SIDE OF THE INVERTER TO PROTECT THE SYSTEM.

LEGEND:

SYMBOL	DESCRIPTION	SYMBOL	DESCRIPTION
	MONOCRSTALLINE PV MODULE		SOLAR INVERTER
	RATED POWER: 410W Max. 41.5V, Imp. 9.77A DIMENSIONS: 440x670x35mm		THREE PHASE HYBRID INVERTER - 120VA
	DOUBLE POLE DC FUSE WITH FUSE HOLDER X REFERS TO THE VOLTAGE RATING (V) Y REFERS TO THE CURRENT RATING (A)		FOUR POLE AC THERMAL-MAGNETIC MINATURE CIRCUIT BREAKER X REFERS TO THE TRIP CURRENT RATING (A)
	DOUBLE POLE DC DISCONNECTING SWITCH X REFERS TO THE CURRENT RATING (A)		FOUR POLE AC SURGE ARRESTER Y REFERS TO THE SURGE ARRESTER TYPE (CLASS) X REFERS TO THE NOMINAL DISCHARGE CURRENT RATING IN (KA)
	DOUBLE POLE DC SURGE ARRESTER X REFERS TO THE SURGE ARRESTER TYPE (CLASS) Y REFERS TO THE NOMINAL DISCHARGE CURRENT RATING IN (KA)		FOUR POLE AC SURGE ARRESTER Y REFERS TO THE SURGE ARRESTER TYPE (CLASS) X REFERS TO THE NOMINAL DISCHARGE CURRENT RATING IN (KA)
	BATTERY BANK NUMBER OF BATTERIES IN SERIES: 24 NUMBER OF BATTERIES IN PARALLEL: 1 BATTERY BANK VOLTAGE: 48V		DOUBLE POLE DC CIRCUIT BREAKER X REFERS TO THE TRIP CURRENT RATING (A)

REVISIONS:

REVISION NO.	DESCRIPTION	DATE
0	ISSUED FOR EXECUTION	25-04-23
1	ISSUED FOR EXECUTION	05-05-23

CONSULTANT:



LCEC Engineering Office, 2nd floor Floor,
Level 5 Bldg, President Elias Hraoui Avenue,
Beirut, Lebanon
Email: energy@lcec.org.lb
Website: www.lcec.org.lb

CLIENT:

GIZ

PROJECT DESCRIPTION:

ROOF PV SYSTEM
GHABOUN

DRAWING TITLE:

SLD

PROJECT PHASE:	DRAWING SCALE:	DRAWING DISCIPLINE:
EXECUTION	NTS	ELECTRICAL